

ID	SIO-DEVICE
30	D0: some High-Speed Reset Routines
31	D1: ATARI810 / ATARI 1050 / ATARI XF551 / Disk drive
32	D2: ATARI810 / ATARI 1050 / ATARI XF551 / Disk drive
33	D3: ATARI810 / ATARI 1050 / ATARI XF551 / Disk drive
34	D4: ATARI810 / ATARI 1050 / ATARI XF551 / Disk drive
35	D5: Disk Drives
36	D6: Disk Drives
37	D7: Disk Drives
38	D8: Disk Drives
39	D9: Disk Drives
3A	D10: SpartaDOS X / RespeQT / IDE+ 2.0
3B	D11: SpartaDOS X / RespeQT / IDE+ 2.0
3C	D12: SpartaDOS X / RespeQT / IDE+ 2.0
3D	D13: SpartaDOS X / RespeQT / IDE+ 2.0
3E	D14: SpartaDOS X / RespeQT / IDE+ 2.0
3F	D15: SpartaDOS X / RespeQT / IDE+ 2.0
40	P1: Printer
41	P2: ATARI 820 40Col. Printer / ATARI 850 paralell port
42	P3: ATARI 1025 80Col. Printer
43	P4: Printer / FujiNet SAM's Printer
44	P5: Printer
45	P6: ATARI 1029 Printer / APE Emulator /Smartdevice
46	P7: Printer / AspeQt/RespeQt Emulator
47	P8: Printer
48	P9: Printer
4F	Type 3/4 poll
50	R1: ATARI 850 Serial Interface
51	R2: ATARI 850 Serial Interface
52	R3: ATARI 850 Serial Interface
53	R4: ATARI 850 Serial Interface
54	W2: AspeQT
55	W3: AspeQT
56	W4: AspeQT
57	W: AspeQT Web Pipe
58	T: ATARI 1030 Modem Serial Interface
59	Y: AspeQT Clipboard
5A	ATR8000 / SALLY CP/M Device
5F	C: Cassette Tape (virtuel OS device)
60	C: Cassette Tape (not real SIO Device)
61	atariserver (AtariSIO) remote control
66	mega-hz Keyboard LED Controller
67	mega-hz SIO-Monitor
6F	DOS2DOS PC Link
70	SIO2USB / FujiNet Control Device
71	Sdrive N1 / FN Network
72	Sdrive N2 /SIO2SD /FujiNet Network
73	Sdrive N3 / SIO2SD /FujiNet Network
74	Sdrive N4 / SIO2SD /FujiNet Network
75	Sdrive N5 / SIO2SD /FujiNet Network

